
NEXIS

YC-S2HS

SDI to HDMI Up/Down Converter







Model Name	SDI to HDMI-S
Description	SDI to HDMI Up/Down Converter
Feature	I ↔ P Conversion (Built-In Interlacer and DeInterlacer.) 60fps ↔ 59.94fps Conversion Frame Rate and Format Up/Down Conversion Power Amplified SDI Loop Out Easy Configuration with Button and OSD Menu

Input Interface	Video SDI×1
Output Interface	Up/Down Converted Video HDMI×1 Loop-Through Video SDI×2
Supported Video Input Format	SDI 1920×1080p@60/50fps HD-SDI 1920×1080p@30/25/24fps 1920×1080i@60/50fps 1280×720p@60/50fps SD-SDI 720×480i@60fps 720×576i@50fps

Supported Video Output Format	HDMI (Up/Down Converted) 1920×1080p@60/50fps 1920×1080p@30/25/24fps 1920×1080i@60/50fps 1280×720p@60/50fps 1280×1024p@60fps 1280×960p@60fps 1024×768p@60fps 800×600p@60fps 640×480p@60fps 720×480p@60fps 720×576p@50fps 720×480i@60fps 720×576i@50fps SDI (Loop-Through) As Input SDI Format
GENLOCK Frame Lock Mode	N/A

Audio Input Format	SDI : Up to 8 Channels, 24bit, 48KHz
Audio Output Format	HDMI/SDI : Up to 8 Channels, 24bit, 48KHz
Plug & Play	✓
DC In	7.5V ~ 15V
Dimension	L:104mm×W:63.6mm×H:26mm