

## Digital Mixer Amplifier with USB, Bluetooth

DMA250G Digital Mixer Amplifier คือเครื่องขยายเสียงมิกเซอร์อเนกประสงค์ ที่รวบรวมฟังก์ชันหลากหลาย เช่น USB flash disk, MP3, FM และ Bluetooth เพื่อความสะดวกในการใช้งาน มาพร้อมช่องต่อเสียง 3 Mic, 2 AUX และ 1 EMC รวมถึงหน้าจอแสดงสถานะที่ชัดเจน มีช่องต่อ EMC IN และ MIC IN พร้อมระบบไฟ Phantom Power เพิ่มความสะดวกสบายในการใช้งาน การออกแบบให้ใช้งานง่ายและเป็นมิตรต่อผู้ใช้ ทำให้อุปกรณ์นี้เหมาะสำหรับการใช้งานในทุกสถานการณ์อย่างลงตัว

# AMP DMA250G



## Features

- With segment code tube screen and intuitive display, more convenient for users to use.
- With built-in Bluetooth, FM and USB function.
- With 3 MIC IN, 1 EMC IN, 2 AUX IN, 1 AUX OUT.
- Support 100V and 70V constant voltage output, and  $4\Omega \sim 16\Omega$  constant resistance output.
- Can be controlled by the infrared remote controller.
- With priority function, and the priority is MUTE>EMC=Alarm=Chime>MIC>Others (When there is an alarm, no chime can be output).
- With master volume control, independent volume control of MIC and AUX, and TREBLE and Bass volume control.
- With MUTE short circuit trigger function which can be remotely controlled by this machine or
- controlled by other devices.
- With power-off memory function.

## SPECIFICATION

|                                   |                                                     |
|-----------------------------------|-----------------------------------------------------|
| <b>Power Supply</b>               | AC200-240V , 50/60Hz                                |
| <b>MIC1 IN Sensitivity</b>        | 10mV $\pm 1$ mV                                     |
| <b>MIC2 IN Sensitivity</b>        | 10mV $\pm 1$ mV                                     |
| <b>AUX1 IN Sensitivity</b>        | 350mV $\pm 50$ mV                                   |
| <b>AUX2 IN Sensitivity</b>        | 350mV $\pm 50$ mV                                   |
| <b>EMC IN Sensitivity</b>         | 350mV $\pm 50$ mV                                   |
| <b>MIC Frequency Response</b>     | 120Hz $\sim$ 12kHz ( $\pm 3$ dB)                    |
| <b>AUX Frequency Response</b>     | 80Hz $\sim$ 15kHz ( $\pm 3$ dB)                     |
| <b>Distortion</b>                 | <1%                                                 |
| <b>Treble</b>                     | 10dB ( $\pm 2$ )                                    |
| <b>Bass</b>                       | 10dB ( $\pm 2$ )                                    |
| <b>Working Temperature</b>        | -10-50°C                                            |
| <b>Relative Humidity</b>          | 20%-80%                                             |
| <b>Rated Output</b>               | 250W                                                |
| <b>Port Output Voltage</b>        | 4-16 $\Omega$ , 70V, 100V (constant-voltage output) |
| <b>Machine Dimensions (D*W*H)</b> | 430x330x88 mm                                       |
| <b>Package Dimensions</b>         | 500x500x165 mm                                      |
| <b>Net Weight</b>                 | 6.8 KG.                                             |
| <b>Gross Weight</b>               | 8.3 KG.                                             |

V1.0.0



บริษัท สยามเทค แอนด์ ดีเวลลอป จำกัด  
16/60 ถ.ติวานนท์ ต.บางพูด อ.ปากเกร็ด จ.นนทบุรี 11120 (สำนักงานใหญ่) โทร. 0-2582-2285  
Website : [www.gygar.com](http://www.gygar.com) | Facebook : Siamtech and Develop | Line Official : @GYGAR | Hotline : 081-618-6780  
สาขาเชียงใหม่ โทร. 063-535-8004 | สาขาขอนแก่น โทร. 081-499-5924 | สาขาหาดใหญ่ โทร. 061-774-9051