MR808
8Port HDMI KVM Switch





Feature:

I. Single USB console control 8 HDMI interface computer and two additional USB device

II. Supports USB TYPE A interface type keyboard and mouse device

III. HDMI standard alone KVM resolution in Max: 4K @30HZ;

IV. Switch the computer through the front panel buttons, keyboard hotkeys and screen menu (OSD)

V. Connect to the controlled device for BIOS-level access without worrying about the risk of viruses and Trojans

VI. The controlled computer does not need to install any software and drivers, and the controlled computer directly recognizes KVM.

VII. Support OSD to set user login mode and increase KVM login security requirements

X. Support widescreen resolution

XI. Support DDC communication to adapt to different graphics devices

XII. Auto scan function monitors all computer operations

XIII. Support for cross-platform operations - Windows, Linux, Mac*, and Sun*

The computer mouse and mouse connection port is controlled by Keep Online technology to simulate the mouse and keyboard. The device is safe and stable, and the switching is fast without delay.

Specification:

Function			8 Ports
Computer Connection			8
Port Selection			OSD Menu, Front panel switches, Hot Key
Connector	Console Connector	Monitor	1 x HDMI Female
		Keyboard	1 x USB Type A Female
		Mouse	1 x USB Type A Female
	PC Connector	Monitor	8 x HDMI Female
		Mouse/Keyboard	8 x USB TYPE B Female
	Power Supply		1 x DC Jack
Toggle switch	Connection Port Selection		8 x keys
	KVM Switch Reset		1 x Semi-embedded keys
LED Instruction	Selected		8 x Green
	Online		8 x Red
Simulation Method	Keyboard & Mouse		USB
Max Resolution Video			4K@30HZ
Scan interval			3、5、10、15、20、30、40、60 seconds（Default 3 Seconds）
Operating Environment	Operating temperature		0-50℃
	Storage temperature		-20-60℃
	Humidity		0-80%RH，No Condensation
PhysicalProperties	Housing		metal
	Dimensions(L x W x H)		432 x 155 x 44 mm
	Weight（kgs）		2.46KG