NEXIS

Power Extender for Digital Discussion System



Model：PE1000

Technical Parameter：

Output voltage +24 V
Rated current: 5A
Current range: 0-5A
Rated power: 120W
Ripple: 120mvp-p
Output accuracy: ±1%
Input voltage range: 90-264v AC; 110-360v DC
Input current: 2A / 115V; 1A / 230V　　Frequency range: 47-63 Hz
Efficiency: 87%
Impulse current :30A@ 230V
Leakage current: < 0 5mA@ 240V
Overload protection: 105 ~ 150%, belching protection, automatic recovery
Short circuit protection: belch protection, automatic recovery
Output overvoltage protection: 30V ~ 33V
Over temperature protection: 110 ℃