MR108

8 Port VGA KVM Switch



- One console controls 8 computers
- Be compatible with USB / PS/2 keyboard and mouse in console and USB keyboard and mouse in computer.
- Support Cascade function;
- Computer selection via front panel switches, hot key and OSD
- It can be updated as remote control by IP card
- Support OSD to set user login mode and increase KVM login security requirements
- Support high video resolution in local and remote IP mode – Support 480i, 480p, 720p, 1080i and 1080p (1920 × 1200)
- Support wide screen resolution
- Support DDC communication, to adapt to a variety of graphics devices
- The Auto Scan function monitors all computer operations
- Support cross-platform operation – Windows, Linux, Mac and Sun, etc.
- Hot pluggable – add or remove computers for maintenance without powering down the switch

SPECIFICATION

Function			8 port
Model			MR108
Computer Connections	Direct		8
	Cascade(Max)		128
CPU Port Selection			OSD Menu, Front Panel, Hot-key
Connector	Console Connectors	Video	1 x VGA DB15 Female Blue
		Keyboard	1 x USB Type A Female, 1x PS2 Female
		Mouse	1 x USB Type A Female, 1x PS2 Female
	Computer Connectors	Video, KB, Mouse	8 x VGA DB15 Female (Blue)
	Power		1 x DC
Key Switch	Connection Port Selection		8 x Button
	KVM Reset		1 x Semi-embedded keys
	IP Module Reset		1 x Semi-embedded keys
	IP Module Default		1 x Semi-embedded keys
LEDs	Computer Selection Port		8 x Green
	On Line		8 x Red
Analog Mode	Keyboard, Mouse		USB, PS2
Video resolution (Max)			1920 x 1200 @ 60HZ
Scan time interval			3, 5, 10, 15, 20, 30, 40, 60s (3s by default)
Operating Environment	Operating temperature		-10˚C~50˚C
	Storage temperature		-20˚C~60˚C
	Humidity		0-80%RH, No Condensation
Physical Properties	Housing		Metal
	Size		432 x 155 x 44 mm
	Weight		1.82KG